

Update GrowControl WiFi Controllers “Beta Version”

Version: ...0.01.15b

Validity: WiFi controllers with a firmware version higher than 0.01.11b.

January 22, 2026 –...0.01.15b

- **Saved access data**

In the old version, it was possible that the access data could no longer be read.

This resulted in the controller's WiFi name and password being reset to a stored default and other access data (home WiFi, GC account) being lost. As a result, the controller could no longer connect and reconnecting was sometimes problematic.

We strongly recommend performing the update, as the described error can occur at any time.

Update procedure:

- The firmware of the WLAN module is updated via the Internet. If your controller is not connected to the server, the update can alternatively be performed via USB stick.

Update instructions WLAN

Standard (via the Internet):

1. In the GUI, go to the SYSTEM tab FIRMWARE section
2. Select the new firmware file under “Firmware update” and click on “Perform update” and then on “Apply”
3. It takes several minutes for the controller to reconnect after the update (status green). The controller must not be disconnected from the network during the update.
4. After the update is complete, the new firmware version is displayed in the SYSTEM section

Alternatively, via USB stick:

1. Place the firmware file on the top level of the file system of a USB stick formatted in FAT32 format.
2. Insert the stick into the USB port on the controller.
3. Restart the controller (unplug the power cord or go to SYSTEM>Restart controller). This is currently necessary to update the list of compatible files on the USB stick.
4. Go to WLAN Info & Settings >> Start WLAN USB Update in the controller menu and confirm with OK.
5. The progress is shown on the display.

Update instructions for main controller:

- Not available for this version. The controller should have version 0.01.14b.